



ANALOGUE Nt mini Pinout:

- 1 - R (composite) - Connect to pin15
- 2 - G (chroma) - Connect to pin11
- 3 - B (luma) - Connect to pin7
- 4 - ground
- 5 - detection
- 6 - ground
- 7 - ground
- 8 - ground
- 9 - not connected
- 10 - detection
- 11 - ground
- 12 - not connected
- 13 - H synch - Connect to pin20
- 14 - V synch
- 15 - detection

ANALOGUE Nt mini sync mode:
Default - sync on composite

Output is DC coupled

SCART Pinout:

- 2 - Audio R - Connect to center pin Audio R
- 4 - Audio ground - Connect to audio ground
- 6 - Audio L - Connect to center pin Audio L
- 5 - B ground - Connect to ground
- 7 - B (luma) - Connect to pin3
- 9 - G ground - Connect to ground
- 11 - G (chroma) - Connect to pin2
- 13 - R ground - Connect to ground
- 15 - R (composite) - Connect to pin1
- 16 - Blanking - Connect to USB pin1 with 180Ω resistor
- 18 - Sync ground - Connect to ground
- 20 - Synch - Connect to pin20

